

R1250i - 1.1kW Inverter Generator





The RATO R1250i inverter generator is the perfect generator to keep on hand ... it is ideal for camping and other recreational activities, as well as running most small appliances with no issue.

With a rated output of 1,000 watts, this quiet and lightweight generator can run for up to 6.5 hours on continuous 1/2 load operation giving you plenty of time to charge phones, keep drinks cold or watch a movie on your laptop while camping.

- Features 4 stroke OHV engine 56cc
 - 2 x built-in USB ports
 - Carry handle for easy movement
 - Low engine oil alarm
 - Spark arrestor
 - Auto decompressor
 - Brushless alternator
 - Lightweight

Specifications	R1250i
Туре	Inverter
Engine model	R56-i
Engine type	Air cooled, 4 stroke, OHV, single cylinder
Starting system	Recoil start
Displacement	56cc
Bore x Stroke (mm)	45 x 35
Compression ratio	8.2:1
Rated frequency	50Hz
Rated voltage	230V
Rated power	1kW
Max. power	1.1kW
DC output	5V / 1.2A
Fuel tank capacity	2.8 litres
Full load continuous running time	3.5 hours
1/2 load continuous running time	6.5 hours
Noise (7m)	68.5dB
Dimensions (L x W x H mm)	370 x 355 x 335
Net weight	12.5kg