

## R2000iS - 2.0kW Inverter Generator





The RATO R2000iS inverter generator is ideal for producing high quality pure sine wave electricity to power all your small electronics and accessories. Being the smallest and lightest in our range, it is perfect to power your favourite equipment and gadgets while on the road!

With a rated output of 1.800 watts, this quiet and lightweight generator can run for up to 6 hours on continuous 1/2 load operation.

The R2000iS features a parallel-in function, meaning two inverter generators, with the same specifications or not, can be in connected with the RATO parallel cable to increase your power.

- Features 4 stroke OHV engine 80cc
  - Spark arrestor
  - Eco throttle function
  - Auto decompressor
  - Fuel gauge
  - Brushless alternator
  - 2 x built in USB ports
  - Independent fuel tap
  - Easy access maintenance door
  - Lightweight and low noise level/ noise insulator
  - Includes battery charging lead

Specifications R200	0iS
<b>Type</b> Inverte	r
Engine model R80-i	
Engine type Air coo	oled, 4 stroke, OHV, single cylinder
Starting system Recoil	start
Displacement 79.7m	I
Bore x Stroke (mm) 48.6 x	43
Compression ratio 8.7 : 1	
Rated frequency 50Hz	
Rated voltage 230V	
Rated power 1.8kW	
Max. power 2.0kW	
DC output 12V / 8	3.3A
Fuel tank capacity 4 litres	
Full load continuous running time 4 hour	S
1/2 load continuous running time 6 hour	S
Noise (7m) 65dB	
Dimensions (L x W x H mm) 498 x	290 x 459
Net weight 22kg	