

## R3000iE - 3.5kW Inverter Generator





The RATO R3000IE inverter generator is ideal for powering your domestic and commercial equipment, from your garden tools to a small compressor and with a handle and wheels, it makes it easy to move around where needed.

With a rated output of 3,200 watts, this quiet generator can run for up to 8,5 hours on continuous 1/2 load operation.

The R3000iE features electronic start operation and a parallel-in function. meaning two inverter generators, with the same specifications or not, can be in joined with the RATO parallel to increase your power.

- Features 4 stroke OHV engine 212cc
  - Spark arrestor
  - Eco throttle function
  - Auto decompressor

  - Fuel gauge
  - Brushless alternator
  - 2 x built in USB ports
  - Independent fuel tap
  - Electric start operation
  - DC output capability
  - Easy access maintenance door
  - 2 x 15 amp outlets
  - Lightweight and low noise level/ noise insulator
  - Wheels and handle for easy movement

Specifications	R3000iE
Туре	Inverter
Engine model	R210-i
Engine type	Air cooled, 4 stroke, OHV, single cylinder
Starting system	Recoil / Electric start
Displacement	212ml
Bore x Stroke (MM)	70 x 55
Compression ratio	9:1
Rated frequency	50Hz
Rated voltage	230V
Rated power	3.2kW
Max. power	3.5kW
DC output	12V / 8.3A
Fuel tank capacity	10 litres
Full load continuous running time	5 hours
1/2 load continuous running time	8.5 hours
Noise (7m)	69dB
Dimensions (L x W x H mm)	645 x 480 x 500
Net weight	46kg