

R8500D-3 - 8.5kW Industrial Generator

The RATO R8500D-3 industrial generator is the tradies best friend and is ready for the worksite. The R8500D-3 comes with a 32 amp IP66 plug and RCD switch making it perfect to run your high output

items, from drills to welders as well as the smaller, more senstive items such as laptops and tablets.

With a rated output of 8.000 watts, this powerful generator can run for up to 7 hours on continuous 1/2 load operation.

- Features 4 stroke OHV engine 499cc
 - 2 x built in USB ports
 - Includes RCD switch
 - AVR rated
 - Includes 32 amp IP66 plug
 - Fuel gauge
 - Independent fuel tap
 - Oil warning system
 - Spark arrestor
 - Auto decompressor
 - Brushless alternator
 - Key start & pull start operation
 - Wheels and handle for easy movement
 - 32 amp socket adaptor available as an accessory

Specifications	R8500D-3
Туре	Inverter
Engine model	R500V
Engine type	Air cooled, 4 stroke, OHV, single cylinder
Starting system	Recoil / Electric start with battery
Displacement	499.6cc
Bore x Stroke (mm)	94 x 72
Compression ratio	8.7 : 1
Rated frequency	50Hz
Rated voltage	240V
Rated power	8.0kW
Max. power	8.5kW
DC output	12V / 8.3A
Fuel tank capacity	25 litres
Full load continuous running time	5 hours
1/2 load continuous running time	7 hours
Noise (7m)	80dB
Dimensions (L x W x H mm)	683 x 540 x 542
Net weight	102kg