

R8750iD - 7.5kW Inverter Generator

Whether you need to run your house during a power outage, or a coffee van and food truck. the highly popular RATO R8750iD open frame inverter generator is the perfect unit for you!

Featuring both electric push button start and pull start operation and with a rated output of 7.000 watts, it can run for up to 10 hours on continuous 1/2 load operation giving you all the power you need to make it through the day/night.

- Features 4 stroke OHV engine 420cc
 - Brushless alternator
 - Smart circuit protection
 - Eco throttle function
 - 2 x built in USB ports
 - Fuel gauge
 - Independent fuel tap
 - Low engine oil alarm
 - Spark arrestor
 - Auto decompressor
 - 3 x 15 amp outlets
 - Electric push button start and pull start operation
 - Antivibration rubber leg stands
 - Wheels and handle for easy movement

Specifications
Туре
Engine model
Certification
Engine type
Starting system
Displacement
Bore x Stroke (mm)
Compression ratio
Rated frequency
Rated voltage
Rated power
Max. power
DC output
Fuel tank capacity
Full load continuous running time
1/2 load continuous running time
Noise (7m)
Dimensions (L x W x H mm)
Net weight
Multi function meter
Breaker
USB device

Receptacle cover

L5-20 120V 20A duplex

Spark arrestor

Oil drain tube

Wheel kit

R8750iD Open frame inverter R420D-i
R420D-i
EPA 3, EMC
Air cooled, 4 stroke, OHV, single cylinde
Recoil / Electric start
420cc
90 x 66
8:1
50Hz
220V
7.0kW
7.5kW
12V / 8.3A
15 litres
6.5 hours
10 hours
84dB
605 x 514 x 537
65kg
yes
3
yes
yes
yes
yes
8" wheels & handle, comes standard
2 x GFCI